
Gas

EPA-Certified for Stationary and Mobile Emergency and Non-Emergency Applications

Ratings Range

		60 Hz
Standby:	kW	240-355
	kVA	300-444
Prime:	kW	275-305
	kVΔ	344-381



Standard Features

- Rehlko provides one-source responsibility for the generating system and accessories.
- The generator set and its components are prototype-tested, factory-built, and production-tested.
- The 60 Hz generator set offers a cULus listing.
- The generator set accepts rated load in one step.
- The 60 Hz generator set meets NFPA 110, Level 1, when equipped with the necessary accessories and installed per NFPA standards.
- A one-year limited warranty covers all generator set systems and components. Two- and five-year extended limited warranties are also available for purchase in some jurisdictions.
- Alternator features:
 - The pilot-excited, permanent magnet (PM) alternator provides superior short-circuit capability.
 - The brushless, rotating-field alternator has broadrange reconnectability.
- Dual fuel model features:
 - Natural gas is the primary fuel. Automatically transfers back to primary fuel when LP fuel becomes low or generator stops and restarts.
 - The patent pending reset box on the generator provides the ability to manually transfer back to natural gas.
 - The natural gas rating is available when running on natural gas.
 - APM603 controller provides load shed for automatic derate to LP ratings to prevent an overload condition.



Generator Set Ratings

					Rich-Burn Natural Gas			Rich-Burn LP Gas (Vapor)	
				130°C Standby			C Rise Rating	130°C	C Rise y Rating
Alternator	Voltage	Ph	Hz	kW/kVA	Amps	kW/kVA	Amps	kW/kVA	Amps
	120/208	3	60	350/438	1216	300/375	1041	240/300	833
	127/220	3	60	350/438	1150	300/375	985	240/300	788
4M4019	120/240	3	60	350/438	1054	300/375	903	240/300	722
	220/380	3	60	305/381	579	275/344	523	240/300	456
	277/480	3	60	350/438	527	300/375	452	240/300	361
	120/208	3	60	355/444	1233	300/375	1041	240/300	833
	127/220	3	60	355/444	1166	300/375	985	240/300	788
5M4027	120/240	3	60	355/444	1069	300/375	903	240/300	722
	220/380	3	60	355/444	675	300/375	570	240/300	456
	277/480	3	60	355/444	535	300/375	452	240/300	361
4M4266	347/600	3	60	355/444	428	305/381	367	245/306	295

RATINGS: All three-phase units are rated at 0.8 power factor. Standby Ratings: The standby rating is applicable to varying loads for the duration of a power outage. There is no overload capability for this rating. Prime Power Ratings: At varying load, the number of generator set operating hours is unlimited. A 10% overload capacity is available for one hour in twelve.

Ratings are in accordance with ISO-8528-1 and ISO-3046-1. Obtain technical information bulletin (TIB-101) for ratings guidelines, complete ratings definitions, and site condition derates.

The generator set manufacturer reserves the right to change the design or specifications without notice and without any obligation or liability whatsoever.

Industrial Generator Set

208-600V

350REZXD

Alternator Specifications

			Alternator
	Specifications		Alternator
	Туре		4-Pole, Rotating-Field
	Exciter type		Brushless, Permanent-
			Magnet Pilot Exciter
	Leads: quantity, ty	pe	12, Reconnectable 4, 600 V
	Voltage regulator		Solid State, Volts/Hz
	Insulation:		NEMA MG1
	Material		Class H, Synthetic,
	Material		Nonhygroscopic
Temperature rise		e	130°C, 150°C Standby
Bearing: quantity, type		type	1, Sealed
Coupling			Flexible Disc
Amortisseur windings			Full
Voltage regulation, no-load to full-load		, no-load to full-load	Controller Dependent
One-step load acceptance		eptance	100% of Rating
Unbalanced load capability		apability	100% of Rated Standby
			Current
Peak motor starting kVA:		g kVA:	(35% dip for voltages below)
	480 V	4M4019 (12 lead)	1750 (60Hz)
	480 V	5M4027 (12 lead)	2200 (60Hz)

4M4266 (4 lead)

1300 (60Hz)

Forged Steel

Electronic

Isochronous

±0.5%

Fixed

Dry

- · NEMA MG1, IEEE, and ANSI standards compliance for temperature rise and motor starting.
- · Sustained short-circuit current of up to 300% of the rated current for up to 10 seconds.
- · Sustained short-circuit current enabling downstream circuit breakers to trip without collapsing the alternator field.
- Self-ventilated and dripproof construction.
- Superior voltage waveform from a two-thirds pitch stator and skewed rotor.
- · Brushless alternator with brushless pilot exciter for excellent load response.

Application Data

			_		
_	-	_	:	-	_
_	n	п	ı	n	ρ
_	••	9	•		·

600 V

Engine Specifications	
Manufacturer	PSI/Doosan
Engine model	PSI18LT
Engine type	18.3 L, 4-Cycle,
	Turbocharged, Charge Air-Cooled
Cylinder arrangement	V-10
Displacement, L (cu. in.)	18.273 (1115)
Bore and stroke, mm (in.)	128 x 142 (5.0 x 5.6)
Compression ratio	10.5:1
Piston speed, m/min. (ft./min.)	511 (1677)
Main bearings: quantity, type	12, Precision Half-Shell
Rated rpm	1800
Max. power at rated rpm, kWm (BHP)	
Natural Gas	422 (566)
LP Gas	297 (396)
Cylinder head material	Cast Iron

Frequency Air cleaner type, all models **Exhaust**

Piston: type, material Crankshaft material

Frequency regulation, no-load to full-load

Frequency regulation, steady state

Valve material Governor: type

Exhaust System	
Exhaust manifold type	Wet
Exhaust flow at rated kW, kg/hr. (cfm)	1492 (2366)
Exhaust temperature at rated kW, dry exhaust, °C (°F)	600 (1112)
Maximum allowable back pressure overall, kPa (in. Hg)	10.2 (3)
Maximum allowable back pressure	
after catalyst, kPa (in. Hg)	5.1 (1.5)
Engine exhaust outlet size, mm (in.)	Flanged Outlet at Catalyst, see ADV drawing

Engine Electrical

Negative
24
45
24
Two, 925
12

ruei	
Fuel System - Rich Burn	
Fuel type	Natural Gas, LP Gas, or Dual Fuel
Fuel supply line inlet	3.0 NPTF
Natural gas fuel supply pressure, kPa (in. H ₂ O) LPG vapor withdrawal fuel supply pressure, kPa (in. H ₂ O)	1.74-2.74 (7.0-11.0) 1.74-2.74 (7.0-11.0)
Dual fuel engine, LPG vapor withdrawal fuel supply pressure, kPa (in. H ₂ O) Fuel supply pressure, measured at the gene downstream of any fuel system equipment a	

Fuel Composition Limits*	Nat. Gas	LP Gas
Methane, % by volume	90 min.	
Ethane, % by volume	4.0 max.	
Propane, % by volume	1.0 max.	85 min.
Propene, % by volume	0.1 max.	5.0 max.
C ₄ and higher, % by volume	0.3 max.	2.5 max.
Sulfur, ppm mass	25 n	nax.
Lower heating value, MJ/m³ (Btu/ft³), min.	33.2 (890)	84.2 (2260)

* Fuels with other compositions may be acceptable. If your fuel is outside the listed specifications, contact your local distributor for further analysis and advice

Application Data

Lubrication

Lubricating System	
Туре	Full Pressure
Oil pan capacity, L (qt.) §	35 (37.0)
Oil pan capacity with filter, L (qt.) §	42.1 (44.5)
Oil filter: quantity, type §	2, Cartridge
Oil cooler	Water-Cooled
C Dabiles reserved as the cost of Dabiles Consider	: £: 4

§ Rehlko recommends the use of Rehlko Genuine oil and filters.

Cooling

Radiator System	
Ambient temperature, °C (°F)*	50 (122)
Engine jacket water capacity, L (gal.)	42 (11)
Radiator system capacity, including engine,	
L (gal.)	177 (46.7)
Engine jacket water flow, Lpm (gpm)	660 (174)
Heat rejected to cooling water at rated kW, dry exhaust, kW (Btu/min.)	365 (20784)
Heat rejected to air charge cooler at rated	
kW, dry exhaust, kW (Btu/min.)	36.2 (2060)
Water pump type	Centrifugal
Fan diameter, including blades, mm (in.)	1321 (52)
Fan, kWm (HP)	20.9 (28)
Max. restriction of cooling air, intake and	
discharge side of radiator, kPa (in. H₂O)	0.125 (0.5)

 Weather and sound enclosures with internal silencer reduce ambient temperature capability by 5°C (9°F).

Operation Requirements

Air Requirements	
Radiator-cooled cooling air,	
m³/min. (scfm)†	820 (29000)
Combustion air, m³/min. (cfm)	1408 (788)
Heat rejected to ambient air:	
Engine, kW (Btu/min.)	55 (3121)
Alternator, kW (Btu/min.)	21 (1195)
† Air density = 1.20 kg/m ³ (0.075 lbm/ft ³)	

Fuel Consumption‡


Natural Gas, m³/hr. (cfh) at % load		Standby Rating
100%		117.0 (4131)
75%		92.0 (3247)
50%		67.8 (2394)
25%		43.5 (1535)
Natural Gas, m³/hr. (cfh) at % load		Prime Rating
100%		102.9 (3635)
75%		78.8 (2784)
50%		55.2 (1949)
25%		33.5 (1182)
LP Gas, m3/hr. (cfh) at % load		Standby Rating
100%		34.3 (1213)
75%		27.7 (977)
50%		21.0 (741)
25%		14.1 (499)
‡ Nominal fuel rating:	Natural gas, 37	7 MJ/m³ (1000 Btu/ft.³)

LP vapor, 93 MJ/m3 (2500 Btu/ft.3)

LP vapor conversion factors:

 $8.58 \text{ ft.}^3 = 1 \text{ lb.}$ $0.535 \text{ m}^3 = 1 \text{ kg.}$ $36.39 \text{ ft.}^3 = 1 \text{ gal.}$

Controllers



APM402 Controller

Provides advanced control, system monitoring, and system diagnostics for optimum performance and compatibility.

- Digital display and menu control provide easy local data access
- Measurements are selectable in metric or English units
- Remote communication thru a PC via network or serial configuration
- Controller supports Modbus® protocol
- Integrated hybrid voltage regulator with ±0.5% regulation
- Built-in alternator thermal overload protection
- NFPA 110 Level 1 capability

Refer to G6-161 for additional controller features and accessories.



APM603 Controller

Provides advanced control, system monitoring, and system diagnostics for optimum performance and compatibility.

- 7-inch graphic display with touch screen and menu control provides easy local data access
- Measurements are selectable in metric or English units
- Paralleling capability to control up to 8 generators on an isolated bus with first-on logic, synchronizer, kW and kVAR load sharing, and protective relays

Note: Parallel with other APM603 controllers only

- Generator management to turn paralleled generators off and on as required by load demand
- · Load management to connect and disconnect loads as required
- Controller supports Modbus® RTU, Modbus® TCP, SNMP and BACnet®
- Integrated voltage regulator with ±0.25% regulation
- Built-in alternator thermal overload protection
- UL-listed overcurrent protective device
- NFPA 110 Level 1 capability

Refer to G6-162 for additional controller features and accessories. Modbus® is a registered trademark of Schneider Electric.

BACnet® is a registered trademark of ASHRAE.

Industrial Generator Set

208-600V

350REZXD

Standard Features

- Alternator Protection
- · Battery Rack and Cables
- Closed Crankcase Ventilation (CCV) with Filters
- Dual Fuel Reset Box (standard on dual fuel models)
- · Integral Vibration Isolation
- Local Emergency Stop Switch
- · Low Coolant Level Shutdown
- Oil Drain Extension
- Operation and Installation Literature
- Secondary Gas Solenoid Valve
- Three-Way Exhaust Catalyst

Available Options

Circuit Breakers Type Rating ■ Magnetic Trip □ 80% Thermal Magnetic Trip **1**00% Electronic Trip (LI) Operation Electronic Trip with Short Manual Manual with Shunt Trip Time (LSI) Electronic Trip with Ground **Electrically Operated** Fault (LSIG) (for paralleling) **Circuit Breaker Mounting**

- □ Generator Mounted
- □ Remote Mounted
- Bus Bar (for remote mounted breakers)

Enclosures for Remote Mounted Circuit Breakers

- □ NEMA 1 (15-5000 A)
- NEMA 3R (15-1200 A)

Approvals and Listings

- □ cULus (UL 2200 and CSA)
- □ Hurricane Rated Enclosure
- □ IBC Seismic Certification

Enclosed Unit

- Sound Enclosure with Internal Silencer (Aluminum)
- □ Sound Enclosure with Internal Silencer (Steel)
- Weather Enclosure with Internal Silencer (Steel)

Open Uni

- ☐ Exhaust Silencer, Critical (Kit includes two silencers)
- ☐ Flexible Exhaust Connector, Stainless Steel (Kit contains two flexible exhaust connectors)

Controller

- Common Failure Relay
- □ Communications Products and PC Software
- ☐ Two Input/Five Output Module (APM402 controller only)
- ☐ Four Input/Fifteen Output Module (APM603 controller only)
- ☐ Pre-Alarms, NFPA110
- □ Remote Emergency Stop
- Lockable Remote Emergency Stop
- □ Remote Serial Annunciator Panel
- ☐ Run Relay (standard with APM603)
- ☐ Manual Key Switch (APM603 controller only)
- Manual Speed Adjust (APM402 controller only)

Cooling System

- Block Heater, 6000 W, 208 V, 1Ph
- ☐ Block Heater, 6000 W, 240 V, (Select 1 Ph or 3 Ph)
- □ Block Heater, 6000 W, 480 V, (Select 1 Ph or 3 Ph) Required for ambient temperatures below 10°C (50°F)
- Radiator Duct Flange

Electrical System

- ☐ Generator Heater
- Battery
- Battery Charger
- Battery Charger Temperature Compensation
- Battery Heater

Fuel System

- Dual Fuel, NG/LPG (Automatic Changeover)
- ☐ Flexible Fuel Lines

(required when the generator set skid is spring mounted)

Gas Filter

Miscellaneous

- □ Air Cleaner Restriction Indicator
- □ Certified Test Report
- Engine Fluids Added
- Rated Power Factor Testing

Literature

- General Maintenance
- ☐ NFPA 110
- Overhaul
- Production


Warranty

- 2-Year Basic Limited Warranty
- 2-Year Prime Limited Warranty
- □ 5-Year Basic Limited Warranty
- □ 5-Year Comprehensive Limited Warranty
- 10-Year Major Component Limited Warranty

Dimensions and Weights

Overall Size, L x W x H, max., 4100 x 2190 x 2464 mm (in.): (161.4 x 86.2 x 97.0)

Weight (radiator model), 4740 (10450) with 4M4019 wet, max., kg (lb.): 4760 (10495) with 4M4266 4980 (10980) with 5M4027



NOTE: This drawing is provided for reference only and should not be used for planning installation. Contact your local distributor for more detailed information.